

T2™ LightMaster Side/Rear

T2 LightMaster is an accessory of externally mounted programmable followspot handles with a control panel and two individual faders that allow you to create a quality follow spot from the T2 Profile™ and T2 Profile FS™ fixtures.



Available in either sideways or back mounted option, the handles feature two programmable faders (for example for dimmer and iris) and a control panel with touch screen display and four custom programmable jog-wheels and ten assignable buttons for a fully-customizeable user experience.

The programmable buttons, jog-wheels and faders allow the operator to comfortably trigger and control dimmer, iris, focus, zoom, frost, colors or other features of the unit. Internal fixture's settings allow you to fully tailor pan/tilt movement behavior by adjusting tension smoothness and resistance.

While in use by a follow spot operator, the remote desk can still take control of all the internal features of the unit (like dimmer, colors etc.).

Quick mounting in back or side position is assured by using quarter turn lock screws. The control panel connects to the unit via USB connection.

Technical Specification

Main features

- Activation button
- Blackout button
- Pan & Tilt freeze buttons
- User setting of controllable attributes
- 4 control jog-wheels
- 2 faders mounted on the handles with direct control of the key features 0-100% (for example dimmer and iris), assignable to any fixture properties (focus, zoom, frost, etc)
- 10 preset buttons with a direct access of the pre-programmed features
- Saving and uploading of custom settings
- Compatible with: T2 Profile™, T2 Profile FS™

Control and programming

- Display: QVGA Robe touch screen with battery backup
- Movement control: manual

Electrical specification and connections

- Power and data in connector: USB B
- Ethernet port in/out: RJ45

Approvals

- CE Compliant
- cETLus Compliant

Mechanical specification

- LightMaster Side:
 - Height: 190.7 mm (7.5")
 - Width: 637 mm (25.1")
 - Depth: 277.5 mm (10.9")
- LightMaster Rear
 - Height: 308.3 mm (12.13")
 - Width: 737 mm (29")
 - Depth: 736 mm (28.9")
- Weight:
 - LightMaster Side: 4 kg (8.8 lbs)
 - LightMaster Rear: 8.3 kg (18.3 lbs)
 - Tripod 6.5 kg (17.2 lbs)
 - Adaptor for tripod 3.6 kg (7.9 lbs)
- Fixation option: On T2 Profile™, T2 Profile FS™

Included items

- Tripod (10980350):
 - Min. height 60 cm (23.6")
 - Max. height 110 cm (43.3")
 - Black colour
- Adaptor for tripod
- Spigot

Optional accessories

- LightMaster Side:
 - Single Top Loader Case: 10120221
- LightMaster Rear:
 - Single Top Loader Case: 10120344

Legal

- T2™ is a Trademark of Robe lighting s. r. o.
- T2™ LightMaster Side and T2™ LightMaster Rear are patented by Robe lighting s. r. o. and are protected by one or more pending or issued patents